## **Three Phase Inverter**

SE3K - SE10K



NVERTERS

## Specifically designed to work with power optimizers

- Noise level suitable for residential environments No external fan
- Superior efficiency (98%)
- Small, lightest in its class, and easy to install
- Built-in module-level monitoring
- Quick and easy inverter commissioning directly from a smartphone using the SolarEdge SetApp
- Internet connection through Ethernet or Wireless (Wi-Fi, ZigBee Gateway, Cellular)
- IP65 Outdoor and indoor installation
- Fixed voltage inverter for longer strings
- Smart Energy Management control



## **/** Three Phase Inverter

SE3K-SE10K<sup>(1)</sup>

	SE3K <sup>(2)</sup>	SE4K <sup>(2)</sup>	SE5K	SE6K <sup>(2)</sup>	SE7K	SE8K	SE9K	SE10K	UNITS
Applicable to inverters with part number	SEXXK-XXXTXBXX4								
OUTPUT									
Rated AC Power Output	3000	4000	5000	6000	7000	8000	9000	10000	VA
Maximum AC Power Output	3000	4000	5000	6000	7000	8000	9000	10000	VA
AC Output Voltage - Line to Line / Line to Neutral (Nominal)	380 / 220 ; 400 / 230								Vac
AC Output Voltage - Line to Neutral Range	184 - 264.5								Vac
AC Frequency	50/60 ± 5								Hz
Maximum Continuous Output Current (per Phase)	5	6.5	8	10	11.5	13	14.5	16	Α
Grids Supported - Three Phase	3 / N / PE (WYE with Neutral)								
Utility Monitoring, Islanding Protection, Configurable Power Factor, Country Configurable Thresholds	Yes								
INPUT									
Maximum DC Power (Module STC)	4050	5400	6750	8100	9450	10800	12150	13500	W
Transformer-less, Ungrounded	Yes								
Maximum Input Voltage	900								Vdc
Nominal DC Input Voltage		750							Vdc
Maximum Input Current	5	7	8.5	10	12	13.5	15	16.5	Adc
Reverse-Polarity Protection				Y	es				
Ground-Fault Isolation Detection	700kΩ Sensitivity								
Maximum Inverter Efficiency			1	9	8	1		1	%
European Weighted Efficiency	96.7	97.3	97.3	97.3	97.4	97.6	97.5	97.6	%
Nighttime Power Consumption				<	2.5				W
ADDITIONAL FEATURES									1
Supported Communication Interfaces <sup>(3)</sup>	RS485, Ethernet, ZigBee (optional), Wi-Fi (requires antenna) <sup>(4)</sup> , Cellular (optional)								
Smart Energy Management	Export Limitation, Home Energy Management (Device Control) With the SetApp mobile application using built-in Wi-Fi access point for local connection								
Inverter Commissioning	\\	With the SetAp	p mobile appl	ication using b	uilt-in Wi-Fi ac	cess point for	local connecti	on	
STANDARD COMPLIANCE									
Safety	IEC-62103 (EN50178), IEC-62109								
Grid Connection Standards <sup>(5)</sup>	VDE 0126-1-1, VDE-AR-N-4105, AS-4777, G83 / G59								
Emissions	IEC61000-6-2, IEC61000-6-3 , IEC61000-3-11, IEC61000-3-12, FCC part15 class B Yes								
				Y	es				
INSTALLATION SPECIFICATION	5		_					_	
AC Output	Cable Gland - diameter 15-21								mm
DC Input	2 MC4 pairs								
Dimensions (HxWxD)	540 x 315 x 191 16.4								mm
Weight Operating Temperature Range	$-40 \text{ to } +60^{(6)}$								kg °C
	-40 to +60%								
Noise	< 40								dBA
Protection Rating	IP65 - Outdoor and Indoor								
Mounting	Bracket Provided								+
(1) For higher power models refer to: https://www.s	l	ites/default/files/	se-three-phase			et ndf			
<ul> <li>(2) Available in some countries; refer to Certification</li> <li>(3) Refer to Datasheets -&gt; Communications categori</li> <li>(4) Wi-Fi connectivity requires an external antenna.</li> <li>(5) For all standards refer to Certifications category</li> <li>(6) For power de-rating information refer to: https://dialable.</li> </ul>	ns category in D ry in Downloads For more inform in Downloads p	ownloads page: I page for specific nation refer to: ht age: http://www.	nttp://www.solare ations of option tps://www.solare solaredge.com/g	edge.com/groups al communicatior edge.com/sites/de groups/support/de	/support/downlo options: http:// efault/files/se-wit ownloads	oads www.solaredge.c		oort/downloads	